

DS Instruments - Step Attenuator (DAT32/64) SCPI Command List V5.0

Command	Example 1	Example 2	Description
ATT x	ATT 30	ATT 12.5	Set the attenuation to x
ATT?			Return current attenuation value
INCR	INCR		Increase by one step
INCR x	INCR 5	INCR 8	Increase by x units
DECR	DECR		Decrease by one step
DECR x	DECR 5	DECR 22.5	Decrease by x units
STEP x	STEP 2	STEP 4	Set the step size to x
STEP?			Return the step size
*IDN?			Return the SCPI identification string
*RST			Reset unit now
*DISPLAY	*DISPLAY OFF	*DISPLAY ON	Power on of off the display
*BUZZER	*BUZZER ON	*BUZZER OFF	Mute the buzzer
*SAVSTATE			Save current value as boot default
*UNITNAME	*UNITNAME Joe		Save a text name for this unit to flash memory
*UNITNAME?			Return this unit name

Version 1.2 - (COM BAUD: 115200)